

DESIGN DRIVEN INSPECTION OR MEASUREMENT

Inventor: Christopher Bevis

TECHNICAL FIELD

[0001] This invention relates generally to inspection or metrology systems and, more particularly, to design driven semiconductor wafer defect inspection or metrology.

BACKGROUND

[0002] Inspection and metrology technologies are conventionally used in semiconductor fabrication facilities for material monitoring, disposition, yield prediction, and yield management. Wafers are inspected at various stages of production using both in-line and off-line processes. Measurement and inspection instruments conventionally require manual interaction for setting up recipes for the instrument.

[0003] Conventional methods for setting up instrument recipes are tedious, error prone, time consuming, and often result in less than ideal data. For example, a typical method requires a human being to draw rectangles or complex polygons by hand on the instrument interface using a mouse or trackball. Another method is for a human being to “mark” the corner of a device feature in the live video image from the measurement instrument microscope and drive the physical stage of the instrument to the next “measurement site” in the x or y direction to enclose the rectangle for inspection (measurement) inclusion or exclusion.

[0004] Current techniques for instrument setup can take anywhere from minutes to several hours and impact the available time an instrument can be used “in production,” which can also affect downstream process tools waiting for a specific measurement—impacting the efficiency of the entire fabrication facility.

[0005] What is therefore needed are systems and methods that improve inspection or metrology instrument performance and reduce the manual interaction required to setup an instrument to improve the precision, accuracy, and efficiency of the fabrication facility.

SUMMARY OF THE INVENTION

[0006] An embodiment of the present invention provides a method for importing a partial or complete pre-existing design file (e.g., GDS2, GDS2 derivative, or equivalent file or data type) and using the content of this file or data to identify and include and/or exclude portions of the complete “die” or series of die (device under inspection) for measurement. Design data is translated or otherwise mapped to the coordinate system of the inspection or measurement instrument allowing specification of, for example, what is and what is not to be measured or inspected, where measurements are to be taken, what features or structures are to be used for alignment.

[0007] The disclosed method and apparatus reduces instrument setup times by analyzing an integrated circuit (IC) design file (gds2, a gds2 derivative, or equivalent data type) directly, indirectly, or translated (including all x,y coordinates of the design features) to produce a format readable by the inspection/metrology instrument. The coordinate system of the measurement instrument and the design data are aligned or mapped, allowing use of targets, structures, features, areas, or regions, etc., from the design information.

[0008] Embodiments of the invention significantly reduce the setup times required to define these targets, structures, features, areas, or regions, for measurement or inspection, and to increase the value of the measurement or inspection in terms of material disposition and/or yield performance predictivity.

[0009] In an embodiment of the invention, the user inputs the contents of a file into the inspection/metrology device. This process can be completely automated using conventions that allow an inspection/metrology system to download the appropriate data

days before or just prior to run time thereby improving the cycle time and overall efficiency of the fabrication facility. The implications on productivity, of not only the measurement systems but all systems downstream of the measurement systems, are profound. The total cost of the capital equipment set of an IC fabrication plant can easily be hundreds of millions of dollars (and increasing dramatically at the 300mm node) with incremental productivity gains of a few percent having tremendous return on the depreciation costs of the equipment set and overall efficiency and throughput (run rate) of the facility.

BRIEF DESCRIPTION OF THE DRAWINGS

[0010] The accompanying drawings, which are incorporated in and constitute a part of this specification, illustrate several embodiments of the invention and, together with the description, serve to explain the principles of the invention.

[0011] FIG. 1 is a block diagram of information flow according to an embodiment of the present invention;

[0012] FIG. 2 is a block diagram of a design driven inspection/metrology system according to an embodiment of the present invention;

[0013] FIG. 3 is a design driven inspection/metrology architecture including a network according to an embodiment of the present invention;

[0014] FIG. 4 is an example of a simplified mask image;

[0015] FIG. 5 is a block diagram illustrating a design driven inspection/metrology flowchart according to an embodiment of the present invention;

[0016] FIG. 6 is a block diagram of a GDS data structure;

[0017] FIG. 7 is a block diagram design of driven process simulation according to an embodiment of the present invention;

[0018] FIG. 8 is an example of a design layout illustrating several features;

[0019] FIG. 9 is a table showing an example of an overlay recipe extraction according to embodiments of the present invention;

[0020] FIG. 10 is an example of a simplified wafer image illustrating alignment sites and measurement sites according to embodiments of the present invention;

[0021] FIG. 11 is a table showing an example of an inspection recipe extraction according to embodiments of the present invention; and

[0022] FIG. 12 is an example of a simplified wafer image illustrating inspection thresholds according to an embodiment of the present invention.

DETAILED DESCRIPTION

[0023] The present invention now will be described more fully with reference to the accompanying figures, in which several embodiments of the invention are shown. The present invention may be embodied in many different forms and should not be construed as limited to the embodiments set forth herein. Rather these embodiments are provided so that this disclosure will be thorough and complete and will fully convey the invention to those skilled in the art. In this disclosure, embodiments include inspection or metrology instruments and inspection and metrology instruments. The term *inspection/metrology* is generally used throughout to encompass each of these embodiments.

[0024] FIG. 1 is a block diagram of information flow according to an embodiment of the present invention. In the illustrated embodiment, behavioral description 105, schematic 110, floorplan 115, and layout 120 are used in the design flow for generating mask set data 125. Behavioral description 105 is code written in, e.g., Verilog, VHDL (Very High Speed Integrated Circuit (VHSIC) Hardware Description Language), or other description language. Schematic 110 is produced from behavioral description 105 by automated or manual techniques, e.g., synthesis or schematic capture. Floorplan 115

represents the overall topology of a design, relative placement of, e.g., modules, global busses, and clocks. Layout 120 describes the geometric representation of, e.g., modules and devices. Mask set data 125 is preferably a file in GDS2 format that represents layout 120. One skilled in the art will appreciate that other design data formats can be implemented, e.g., GDS, GDS2 derivative, CATS, or equivalent file or data type. Mask set data 125 optionally includes designer intent information derived directly or indirectly from behavioral description 105, schematic 110, floorplan 115, layout 120, or other parts of the design information flow. One skilled in the art will appreciate that each of, e.g., behavioral description 105, schematic 110, and floorplan 115 need not be used in producing mask set data 125.

[0025] From mask set data 125, mask writer 130 produces mask set 135 using techniques known to those skilled in the art. Stepper setup file 140 defines how stepper 145 exposes wafer 160 for a given mask in mask set 135. Stepper setup file 140 includes, e.g., focus and exposure settings, blading, and die placement data. Recipe extraction system 150 performs analysis to recognize regions or target areas from mask set data 125. In an embodiment of the present invention, recipe extraction system 150 uses die placement data from stepper setup file 140 in conjunction with at least a portion of mask set data 125 to generate inspection/metrology recipe 155. A recipe is a set of instructions including wafer processing parameters, inspection parameters, or control parameters for telling an inspection/metrology system how to inspect/measure a wafer. In another embodiment of the present invention, recipe extraction system 150 performs analysis using behavioral description 105, schematic 110, floorplan 115, layout 120, or other design data. For example, recipe extraction system 150 uses specifications for the process and analyzes a layout 120 data file, rather than mask set data 125 in preferably GDS2 format.

[0026] Mask set data 125 is a partial or complete pre-existing design file (e.g., GDS2, GDS2 derivative, CATS, or equivalent file or data type). Further details of mask set data 125 are discussed below and with reference to FIG. 6. Table 1 lists examples of the types of information available from mask set data 125. Recipe extraction system 150 is preferably implemented by software code executing on a general-purpose computer,

but can be implemented in, e.g., a special-purpose computer, or hardware. Further details of the recipe extraction processes and apparatus are provided throughout this disclosure. Inspection/metrology recipe 155 contains at least information that inspection/metrology tools 165 need for running the appropriate inspection/metrology tests on a wafer at a given process level. Inspection/metrology recipe 155 preferably contains data required for each of several inspection/metrology instruments as is typically used in semiconductor fabrication. For example, inspection instruments available from KLA-Tencor Corp. of San Jose, CA include patterned wafer micro inspection station (model 2139), patterned wafer macro inspection station (model 2430), and patterned wafer darkfield inspection station (model AIT III). Metrology instruments also available from KLA-Tencor Corp. of San Jose, CA include film measurement tool (model F5), critical dimension measurement tool (model 8450 CD SEM), and overlay measurement tool (model Archer 10).

Table 1.

Alignment sites, targets, or structures
Inspection areas (regions of the device to be inspected); masked areas (regions of the device NOT to be inspected)
Measurement sites, targets, or structures
Regions of uniform makeup, material, density, and topography
Critical measurement sites, targets, or structures that have a direct bearing on device performance
Cell-to-cell calculation targets or areas
Regions identified for cell-to-cell inspections
Reticle identification sites
Critical Dimension measurements sites, targets, and structures
Film measurement targets, sites, and critical areas for measurement
Registration sites, structures, and targets for determining layer-to-layer overlay measurements, tolerances, and errors

[0027] By way of further example, several embodiments are now described for various inspection/metrology testing operations.

Device Inspection

[0028] Optical, electron beam, x-ray, or other inspection systems acquire information from mask set data 125 either directly or indirectly, or through translation of the design data in inspection/metrology recipe 155, with or without employing a

computer for translation. The acquired information includes, for example alignment sites, targets, or structures, inspection areas (regions of the device to be inspected), masked areas (regions of the device NOT to be inspected), or regions of uniform or non-uniform makeup, material, density, and topography for the purpose or region based processing, cell-to-cell calculation targets or areas, regions identified for cell-to-cell inspections or other types of inspection, or regions, sites, structures, or areas associated with specific illumination conditions (light level boxes, filters, polarization states, spatial filter calculations, light stops, etc) or collection channels including filters, polarization states, aperture settings, etc., including structures whose critical measurement may have a direct bearing on understanding eventual device performance, etc.

Critical Dimension Measurement

[0029] Optical, electron beam, x-ray, or other critical dimension (CD) measurement systems acquire information from mask set data 125 including alignment sites, targets, or structures, critical dimension measurement sites, targets, or structures including structures whose critical measurement and analysis may have a direct bearing on understanding eventual device performance, etc.

Overlay Measurement

[0030] Optical, electron beam, x-ray, or other overlay measurement systems acquire information from mask set data 125 including alignment sites, targets, or structures, registration sites, structures, and targets for determining layer-to-layer overlay measurements, tolerances, and errors, including structures whose critical measurement and analysis may have a direct bearing on understanding eventual device performance, etc.

Film Measurement

[0031] Optical, electron beam, x-ray, or other film measurement systems acquire film measurement targets, sites, and structures, including structures whose critical measurement and analysis may have a direct bearing on understanding eventual device performance, etc.

[0032] For example, with further reference to FIG. 1, a film thickness test is described. Recipe extraction system 150 reads mask set data 125 to identify regions on the wafer that have the appropriate film structures for a given measurement. In another embodiment, a three-dimensional representation of film structure is used to identify film measurement regions. Additionally, designer intent, target sites, critical areas, or instances of named structures present in the design data may be used in the analysis process. Stepper setup file 140 is then integrated with mask set data 125 to translate the coordinate system and determine die placement on the wafer for the identified uniform areas. Inspection/metrology recipe 155 is created to instruct the film measurement instrument to test appropriate areas of the wafer for film thickness.

[0033] FIG. 2 is a further block diagram of a design driven inspection/metrology system according to an embodiment of the present invention. In the illustrated embodiment, design data 210 is imported to inspection/metrology instrument 220. Design data 210 includes mask set data 125 (FIG. 1) and, optionally, data from stepper setup file 140. Among other functional units and data collection tools (not shown in FIG. 2), inspection/metrology instrument 220 comprises an integrated recipe extraction system 230 and corresponding recipe 240. Recipe extraction system 230 performs the particular analysis on design data 210 that is required to generate recipe 240 appropriate for inspection/metrology instrument 220. That is, for a given inspection/metrology test, a particular subset of design data 210 may be relevant. For example, design data 210 preferably includes information relating to the multiple layers of the production process. Inspection/metrology instrument 220 can, for example, require information about regions of a particular layer of design data 210. Recipe extraction system 230, therefore, performs the particular analysis required for inspection/metrology instrument 220. Recipe extraction system 230 eliminates or reduces the need for manual instrument time, thereby improving the productivity and availability of the tool for "in-line," repetitive, unique, or sequenced "production," measurements, and other types of measurements supporting the engineering and production activities associated with a fabrication line.

[0034] FIG. 3 is a design driven inspection/metrology architecture including a network according to an embodiment of the present invention. Design data management

system 310, recipe extraction system 320, recipe management system 330, and inspection/metrology instrument 340 are operatively coupled via network 350. In a preferred embodiment, network 350 is a local area network running a switched ethernet protocol. Of course, other types of networks including metropolitan, wide area, or wireless networks may be used.

[0035] Design data management system 310 is preferably a file library of mask set data. Of course, design data management system 310 can also be a database or other appropriate data store. Design data management system 310 includes design data representing, for example, a plurality of layers of an integrated circuit layout, a plurality of devices, schematic data, layout verification data, and designer intent data. In addition to the data types just enumerated, one skilled in the art will appreciate that design data management system 310 can store or retrieve any type of data used in the design process. Recipe extraction system 320 preferably interfaces with at least design data management system 310 and recipe management system 330. Recipe extraction system 320 retrieves and processes design data from design data management system 310. In a preferred embodiment, recipe extraction system 320 produces recipes that are stored in recipe management system 330. Inspection/metrology instrument 340 retrieves recipes appropriate for a single test or suite of tests from recipe management system 330. One skilled in the art will appreciate that although a single inspection/metrology instrument is illustrated in FIG. 3, several such instruments can be coupled via network 350 or other networks (not shown).

[0036] Design data management system 310 enables “off-line” (i.e., not on a specific, physical inspection or measurement system) interaction with design data which improves the productivity of “on-line” in-fab inspection and measurement systems. The design driven data inspection/metrology is dramatically faster and more accurate because the operation is preferably software driven, thereby eliminating manual interaction with physical stages and the associated errors. A direct translation of the coordinates are selected and used at the “micro” level rather than a manual, macro-level interaction with trackballs, mouses, stages, display devices, etc. Moreover, in an embodiment, this process can be automated for specific layers (or content) of the design data (e.g., GDS2

file or equivalent data files or types) greatly simplifying setup and improving the productivity of all downstream process systems which may be dependent upon the results of these inspection and measurement systems.

[0037] The architecture illustrated in FIG. 3 provides several benefits. Recipe management system 330 performs central storage and/or delivery functions that make the availability, translation, and integration of these design data types more accessible to the inspection/metrology systems. Furthermore, a single setup session, including one to many design layers, allows identifying inspection areas and measurement points within the device for a wide variety of measurement and inspection systems—thereby streamlining the process for a variety of measurements simultaneously. Throughput (run rate) of the inspection/metrology device is improved by generally reducing the inspected or measured area to that which is of the highest value, thereby reducing the processing overhead (and run rate) of the inspection/metrology system. By reducing the data to only that which is directly relevant to a specific layer or layers, the quality and accuracy of the data is increased for the purpose of material disposition and predicting yield or eventual device performance. Table 2 includes examples of inspection/metrology instrument performance improvements at several measurement points in the fabrication process.

Table 2.

Region Based Multi-thresholding (RBMT)	Resolution is limited by the patience of the applications engineer (or customer) to go through the process of drawing multiple boxes on the instrument interface during setup. An embodiment of the invention allows setting up at full resolution (of the design data) for any given layer without the necessity of manually manipulating the data, i.e., only inspecting the contacts or vias of a specific step. This is of higher value than inspecting regions that do not impact the performance or yield of the device at that step and reduces the time it takes to define this information.
Segmented Auto-Thresholding (SAT)	Template performance is improved if the acquired raw data is only from specific portions on the design (i.e., only the contacts, or only the polysilicon lines).
Recipe Automation	Recipes are automated with an instrument or recipe management system acquiring the appropriate layer

	information from the design file well ahead of material arriving for measurement at any given step in the fabrication process—potentially even before start material is introduced into a fabrication facility for a given IC design/product.
Post Processing	Reporting of defects for critical areas within a specific layer of a device allows for improved yield predictivity and “kill ratio” calculations for yield predictivity and in-line device performance monitoring. Image processing algorithms, including automated defect classification, can be used in conjunction with design information to provide additional precision and resolution to results.
“Cell-to-cell” Setup	The design data for a given memory cell device allows optimizing “cell size teach” offline.

[0038] FIG. 4 is an example of a simplified mask image. FIG. 4 illustrates several elements, such as, row driver array 405, column driver array 410, DRAM (dynamic random access memory) cell array 415, overlay target 420, and alignment site 425 at a particular process level. Table 3 is a simplified mask set data description corresponding to the mask image of FIG. 4.

Table 3.

Instance Type	Element Name	Mask data	
		Origin	Pitch
Array[1,10]	Row Driver	(50 μ m, 25 μ m)	(0 μ m, 5 μ m)
Array[10,1]	Column Driver	(50 μ m, 25 μ m)	(5 μ m, 0 μ m)
Array[10,10]	DRAM Cell	(25 μ m, 25 μ m)	(5 μ m, 5 μ m)
Instance	Overlay Target	(60 μ m, 0 μ m)	
Instance	Alignment Site	(0 μ m, 0 μ m)	

[0039] In a preferred embodiment of the present invention, element names and instance types in the design data are used for identifying, e.g, repetition, target areas, and other items listed in Table 1. Further details of identifying structures are discussed below and with reference to FIGS. 9 and 11. In another embodiment, pattern recognition is used for identifying inspection or metrology items, such as those listed in Table 1.

[0040] FIG. 5 is a block diagram illustrating a design driven inspection/metrology flowchart according to an embodiment of the present invention. In the illustrated embodiment, design data is used for configuring a spatial filter. Recipe extraction system 510 performs steps 515, 520, and 525. In step 515, design data is received or read into the analyzer. In step 520, a Fourier analysis is used to find the periodicity of the design data. One skilled in the art will appreciate that other mathematical methods can be used to detect and to map regions of periodic data. In step 525, parameters are extracted from the design data. Parameters include, for example, recipe items and machine setup items. In the illustrated embodiment, an object of extracting parameters is determining the spatial filter configuration.

[0041] Recipe extraction system 510 communicates with inspection/metrology instrument 550. Recipe extraction system 510 optionally produces a recipe (not shown) that can be used "off-line," i.e., data analysis is completed before inspection/metrology instrument 550 is ready for testing instructions. In the illustrated embodiment, inspection/metrology instrument 550 performs a test requiring spatial filtering of a collector to remove scatter from repetitive patterns, further increasing signal-to-noise on critical defects. Programmable spatial filter 560 includes parameters of periodicity 565, wavelength 570, angle of incidence 575, and spot size 580. Periodicity 565 is derived from step 520 of recipe extraction system 510. Wavelength 570, angle of incidence 575, and spot size 580 are illumination parameters known to inspection/metrology instrument 550. The use of design data, therefore, automates the programming of a spatial filter.

[0042] FIG. 6 is a block diagram of a GDS file structure. GDS files describe the images on each mask of a mask set. As illustrated in FIG. 6, a GDS file has at least a header 610, library 620, and mask data 630. Header 610 includes, e.g., information on die size. Library 620 includes named definitions of macros for each type of element as a set of polygons. Mask data 630 includes locations on the mask of elements defined in library 620. Objects in library 620 are assigned to layers that correspond to wafer processing steps. Table 4 is an ASCII representation of an example GDS data file.

Table 4.

HEADER

3
BGNLIB
96
2
2
14
1
37
96
2
2
14
1
37
LIBNAME EXAMPLELIBRARY
GENERATIONS
3
UNITS
1.0000000000000E-03
1.0000000000000E-09
BGNSTR
96
2
2
14
1
0
96
2
2
14
1
17
STRNAME EXAMPLE
BOUNDARY
LAYER
1
DATATYPE
0
XY
-10000
10000
20000
10000
20000
-10000

```
-10000  
-10000  
-10000  
10000  
ENDEL  
ENDSTR  
ENDLIB
```

[0043] FIG. 7 is a block diagram of design driven process simulation according to an embodiment of the present invention. In this embodiment, design data 710 is input to process simulator 720 to produce measurement sensitivities 730. Process simulator 720 simulates the physical parameters of design data 710 at various stages in the fabrication process and creates corresponding measurement sensitivities. For example, process simulator 720 can create measurement sensitivities based on the design data and properties of how a polysilicon line should appear on a wafer in a given process step. Determining appropriate measurement sensitivities for each test of an inspection/metrology system can completely automate the wafer monitoring and inspection process, thereby increasing fabrication throughput. Process simulator 720 is preferably software available from Synopsys, Inc. of Mountain View, CA. One skilled in the art will appreciate that any software or hardware that simulates wafer processing would be appropriate.

[0044] In another embodiment, multiple layers of design data (e.g., gds2, gds2 derivative, or equivalent file or data type) are used to simulate device structure for the purposes of inspection/metrology device optimization. That is, analysis of design data may incorporate components of structure rendering or simulation to provide analysis that can be used, for example, to optimize data collection by the inspection/metrology instrument. Further, inspection/metrology instruments can include image analysis and automatic defect classification based on, for example, targets, structures, or features referenced from the design data. In a preferred embodiment, a combination of yield or device performance feedback is used in conjunction with design data to determine critical inspection/metrology structures or areas which then drive the optimization of the inspection/metrology instrument for improved performance.

[0045] FIG. 8 is an example of a design layout illustrating several features. FIG. 8 illustrates a device with multiple layers of design information. The design data analysis processes and apparatus described herein use one or more of these layers to extract parameters and generate recipes for inspection/metrology instruments. Elimination of extraneous device features (noise sources) allows focusing measurements or inspections on those structures that have the most value for the specific layer (or layers) under measurement or inspection. For example, for a given inspection test, the specific patterns and geometries in the contact layer data may be most relevant. Thus using one or more layers of design data reduces setup definition and programming times, and increases the accuracy of collected data or defect classification.

[0046] FIG. 9 is a table showing an example of an overlay recipe extraction according to embodiments of the present invention. In FIG. 9, methods are described for extracting recipe items including alignment sites, measurement sites, measurement info, and target value. The illustrated alignment sites method 905 is now described in further detail. Alignment sites are preferably used to setup properly coordinates to drive to measurement sites. In step 1, the mask set data is searched for structure types. Structure types include named alignment site elements (e.g., 425, FIG. 4), any structure specifically or empirically found useful for alignment, or pattern recognition of alignment targets. In step 2, the locations of the alignment structures are determined relative to die origin. In step 3, the locations of the alignment structures are translated to locations on the wafer using, e.g., a stepper setup file. In step 4, the locations closest to the 3 o'clock and 9 o'clock positions (1010, FIG. 10) are preferably selected. Opposite ends of the wafer are preferably used for alignment sites, although one skilled in the art will appreciate that other locations may be selected.

[0047] In overlay metrology, measurement sites 910 are used to determine the degree to which one layer aligns with prior process steps. Measurements are preferably made using the conventional 9 site pattern to determine variation across the wafer. As illustrated in FIG. 9, step 1 of extracting a measurement site recipe is searching mask set data for structure types. Structure types include named overlay targets (e.g., 420, FIG. 4), specific devices or transistors, or other structures useful for overlay measurement. In step

2, the locations of the measurement sites are determined relative to the origin. In step 3, the locations of the measurement sites are translated to locations on the wafer using, e.g., a stepper setup file. In step 4, the locations closest to the 9 site pattern (1020, FIG. 10) are preferably selected. In another embodiment, several locations (e.g., one to five) are selected on a given die for measuring the same type of device. For example, designer intent can be used to identify a critical structure that is measured in several locations on a given die or across the wafer.

[0048] For other measurement site types, measurement information 915 is extracted. In a preferred embodiment, site types are identified by name in the mask set (design) data. In another embodiment, pattern recognition is used to identify site types. Once identified, a lookup table or database is used to determine the measurement strategy and corresponding recipe data. In some cases, knowledge of the desired shape of a structure is necessary to select the magnification of an optical system or the algorithm to be used in analyzing the data to produce a measured data value. A target value 920 is determined from geometry information for a measurement site. In some cases, the overlay value on a transistor structure accommodates the fact that the desired location of the source or drain structures are not intended to be centered on the transistor's active region. A method for extracting target value recipe information includes using the geometry data from the mask set data to derive target value.

[0049] FIG. 10 is an example of a simplified wafer image illustrating alignment sites and measurement sites according to embodiments of the present invention. Alignment sites 1010 are used to setup coordinates for precise location of measurement sites. Alignment sites 1010 are illustrated in the 3 o'clock and 9 o'clock positions on the wafer. One skilled in the art will appreciate, however, that alignment sites are typically on opposite ends of the wafer but can be selected from a plurality of appropriate locations and structures. Measurement sites 1020 are used to determine the degree to which one layer aligns with prior process steps. FIG. 10 illustrates a 9 site pattern that is distributed across the wafer. Distributed measurement patterns are used for determining variations across the wafer.

[0050] FIG. 11 is a table showing an example of an inspection recipe extraction according to embodiments of the present invention. In FIG. 11, methods are described for extracting recipe items including alignment sites, machine setup, region based thresholding, and programmable spatial filter setup. The illustrated alignment sites method 1105 is now described in further detail. Alignment sites are preferably used to setup properly coordinates to drive to inspection sites. In step 1, the mask set data is searched for structure types. Structure types include named alignment site elements (e.g., 425, FIG. 4), any structure specifically or empirically found useful for alignment, or pattern recognition of alignment targets. In step 2, the locations of the alignment structures are determined relative to die origin. In step 3, the locations of the alignment structures are translated to locations on the wafer using, e.g., a stepper setup file. In step 4, the locations closest to the 3 o'clock and 9 o'clock positions (1010, FIG. 10) are preferably selected. Opposite ends of the wafer are preferably used for alignment sites, although one skilled in the art will appreciate that other locations may be selected.

[0051] Machine setup recipe extraction 1110 is now described based on the example illustrated in FIG. 11. Process level data are those parameters that change from process level to process level in a given product. Process level data describes, e.g., registration, alignment, data collection, exclusion, and inspection criteria. In step 1, the process level is determined from the mask level name in the mask set data. One skilled in the art will appreciate that other strategies exist for determining the process level, such as, directly encoding a process level ID (identifier) or mask ID in the mask set data. In step 2, a lookup table or database is used to determine, e.g., laser power and gain. For each process layer, a lookup table includes parameters and corresponding values. Example parameters include data collection channel selection, illumination polarization, APS (automatic positioning system) reflectivity, gain/sensitivity, variable aperture stop, collection polarization, contrast, and other parameters used in the processing of the acquired data either in software or hardware. One skilled in the art will appreciate that the APS is an opto-electronic system that servos the height of the wafer during scanning. In an alternate embodiment, analysis of the expected structures on the wafer determined by process simulation are used in place of the lookup table to determine appropriate

machine setup parameters. Process simulation is described above and with respect to FIG. 7.

[0052] Region based thresholding 1115 is preferably used to increase defect capture where there are distinct scattering differences in differentiating specific regions of a device; that is, embedded cache in logic devices, bus versus array in memory devices, or embedded memory devices. Mask set data is used to identify areas where high sensitivity is achievable based on the pattern expected on the wafer and to set thresholds accordingly. As illustrated in the example of FIG. 11, step 1 is to determine array regions by looking for array instances in the mask set data. Step 2 is to determine open areas by generating estimated image on wafer. Step 3 is to set threshold for these areas accordingly. In step 4, the thresholds are duplicated over all die using stepper setup file information. One skilled in the art will appreciate that this method can be used to estimate the achievable sensitivity for each region of similar makeup by searching mask set data for named instances or performing pattern recognition.

[0053] Programmable spatial filter (PSF) settings 1120 can be extracted to generate optimal suppressing of pattern and increase defect capture. In step 1, an expected wafer image is generated from mask set data. Next, in step 2, a Fourier transform is performed on the image using conventional techniques. In step 3, PSF pattern settings are generated based on peaks in the Fourier transform. Further detail on PSF settings is described above and with reference to FIG. 5.

[0054] FIG. 12 is an example of a simplified wafer image illustrating inspection thresholds according to an embodiment of the present invention. Threshold 1 (1205), threshold 2 (1210), and masked 1215 regions are illustrated. As discussed above and with respect to FIG. 11, separate thresholds are defined for regions of different background noise levels within a die. The use of at least threshold 1 (1205) and threshold 2 (1210) optimizes defect capture in complex designs. Masked region 1215 is a region that is not inspected. The use of masked region 1215 improves the throughput of an inspection/metrology instrument by reducing the inspected or measured area to that of the highest value.

[0055] Having described preferred embodiments of design driven inspection/metrology (which are intended to be illustrative and not limiting), it is noted that modifications and variations can be made by persons skilled in the art in light of the above teachings. It is therefore to be understood that changes may be made in the particular embodiments of the invention disclosed that are within the scope and spirit of the invention as defined by the appended claims and equivalents.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
2223
2224
2225
2226
2227
2228
2229
22